



Westinghouse

INNOVATION YOU CAN BE SURE OF

iGen4500s

Digital Inverter Generator

Westinghouse digital inverter generators offer you the ultimate in portable power convenience. Lightweight, fuel efficient and quiet, their mains-quality electrical output can safely power all of your sensitive electronic equipment. They're an essential part of your gear for caravanning and camping and also great for home as a backup power supply.

Features and Benefits

Powerful

4,500 Watts maximum output is the highest in its class to run more of your electrical devices.

Effortless Starting

Strain-free electric starting at the push of a button on the generator or remote control.

Portable

Ergonomic lifting handles and Never-Flat wheels allow you to safely move it about with ease.

Quiet

Ultra-silent running from only 51 dB(A) that won't disturb you or your neighbours.

Long Running

Up to 24 hours achieved by its fuel-efficient engine and biggest-in-class 13.5 L fuel tank.

Easy To Use

Yellow-coloured touch points guide you to the controls required for normal operation.

Mains Quality Electricity

Digital inverter technology safely powers all of your sensitive electronic equipment.

Clean Air Technology

4-stroke OHV petrol engine with Australian and US EPA compliant emission controls.

Plug and Play

Everything you need is in the box. No assembly required. Just add petrol.

Warranty Protection

2-year domestic use warranty to safeguard your investment (conditions apply).

3700/4500

RUNNING WATTS

STARTING WATTS



Control Panel Functions

240-Volt AC, 15-Amp Outlet with Cover

12-Volt DC, 8-Amp Accessory Socket with Cover

Frame Terminal for earthing

Engine Control Switch

ECO Throttle Control to minimise fuel consumption



Output Indicator

Overload Alarm

Low Oil Alarm

Fuel Control Switch

USB Fast Charge Outlet with Cover

Data Center

0168 07:10

Cumulative Run Time (hours) Run Time to Empty (hours)

P2.80 12.9L

Output Power (kW) Fuel Level (litres)

U240

Output Voltage (Volts)

Reset Button

Power - when you need it - where you need it

Specifications

iGen4500s

ENGINE		240 VOLT AC ELECTRICAL	
Type	1-Cylinder, 4-Stroke, Overhead Valve, Air Cooled	Voltage (V)	240
Displacement (cc)	224	Frequency (Hz)	50
Maximum Speed (rpm)	3,600	Number of Phases	1
Oil Capacity (mL)	600	Continuous Running Power (W) *	3,700
Low Oil Shutdown	Yes	Maximum Starting Power (W)	4,500
Spark Plug	Torch F7RTC	Continuous Running Current (A)	15.4
Fuel	Unleaded Petrol	Voltage & Waveform Control	Digital Inverter, Pure Sine Wave Output
Fuel Tank Capacity (L)	13.5	Total Harmonic Distortion (THD)	< 2.5%
Fuel Gauge	Yes	Receptacles	2 x 15 A, IP44
Auto-Speed Eco Throttle	Yes	Overload Protection	Electronic
Starting Methods	Electric / Remote and Recoil	Alternator	Brushless, Permanent Magnet
Battery	12 V, Maintenance Free	Output Meter	Digital, Multi-Function
Hour Meter	Yes	12 VOLT DC ELECTRICAL	
Run Time @ 700 / 2,800 W	19 / 7.5 hours	Voltage (V)	12
Noise Level @ 700 / 2,800 W	52 / 62 dB(A) @ 7m	Maximum Current (A)	8
DIMENSIONS		Maximum Power (W)	100
Length (mm)	650	Receptacle	8 A, IP44
Width (mm)	480	5 VOLT DC ELECTRICAL	
Height (mm)	520	Voltage (V)	5
WEIGHT		Maximum Current (A)	2.1
Weight - Dry (kg)	49.5	Maximum Power (W)	10
Weight - Wet (kg)	60	Receptacle	USB Type A, IP44

* Rated output at 1.0 power factor.

